



# **MSR Gold™ FastFit**

## MSR Gold™ 2000/1 FastFit 1CT/8

All lamps burn out eventually, but when this happens with single ended MSR Gold™ FastFit, it is replaced in seconds – thanks to the specially designed lamp base and lamp holder. This lamp provides a high beam intensity of pure, white light for a truly illuminating performance, while the gold-plated caps provide superior heat protection and prevent premature failure. P3 technology allows use in any position and at higher temperatures, further extending lamp life and consistency of high-quality light output. Also, because the FastFit design is applied to Philips Halogen lamps, switching between lamp technologies can be done quickly and easily. The Philips MSR GoldTM FastFit can be operated in a lamp wattage range between 700W and 2500W.

#### **Product data**

General Information	
Cap-Base	PGJX50 [ PGJX50]
Operating Position	UNIVERSAL [ Any or Universal (U)]
Main Application	Entertainment
Life to 50% Failures (Nom)	750 h
Light Technical	
Luminous Flux (Min)	155000 lm
Luminous Flux (Nom)	172000 lm
Chromaticity Coordinate X (Nom)	329
Chromaticity Coordinate Y (Nom)	333
Correlated Color Temperature (Nom)	5700 K
Luminous Efficacy (rated) (Nom)	86 lm/W
Color Rendering Index (Nom)	90
Operating and Electrical	
Power (Rated) (Nom)	2000 W

Lamp Current (Nom)	18.2 A
Ignition Supply Voltage (Max)	198 V
Controls and Dimming	
Dimmable	Yes
Mechanical and Housing	
Cap-Base Information	PGJX50
Luminaire Design Requirements	
Bulb Temperature (Max)	950 ℃
Pinch Temperature (Max)	500 °C
Product Data	
Full product code	871869667944900
Order product name	MSR Gold™ 2000/1 FastFit 1CT/8
EAN/UPC - Product	8718696679449

Datasheet, 2019, May 13 data subject to change

### MSR Gold™ FastFit


Order code	928410105114	
Numerator - Quantity Per Pack	1	
Numerator - Packs per outer box	8	
Material Nr. (12NC)	928410105114	

Net Weight (Piece)	138.000 g	
--------------------	-----------	--

#### **Warnings and Safety**

• A lamp breaking is extremely unlikely to have any impact on your health. If a lamp breaks, ventilate the room for 30 minutes and remove the parts, preferably with gloves. Put them in a sealed plastic bag and take it to your local waste facilities for recycling. Do not use a vacuum cleaner.

#### Dimensional drawing



MSR Gold 2000/1 FastFit

Product	D (max)	0	L (min)	L	L	C (max)	F
MSR Gold™ 2000/1	34 mm	8 mm	66 mm	68 mm	67 mm	134 mm	50 mm
FastFit 1CT/8							

